
INKER & MASOR

MODEL



PIPE & CABLE SHORT LOCATOR

For locating electrical HOLIDAY shorts and open couplings DETECTOR on underground pipelines

The Model PD Oscillator's audio frequency on a pipe allows the Receiver to:

- Locate pipe, buried or submerged
- Find depth of pipe
- Find shorts and open couplings
- Locate buried insulators
- ECDA tool for locating holidays and voids in coatings on buried pipe



Distributed by

MESA PRODUCTS INC. 4445 S. 74th E. Ave. Tulsa, OK 74145 Phone: 918-627-3188

1-888-800-MESA



NULL Pearson Method

AVAILABLE FROM STOCK!

www.teststations.com

www.detectron.com



www.tinker-rasor.com

Info@tinker-rasor.com



Tinker & Rasor quality is found in our products, our people and our customer service.





CORROSION MITIGATION INSTRUMENTATION

PRODUCT DATA SHEET MODEL PD LOCATOR/HOLIDAY DETECTOR

Features:

- Audio frequency
- Up tp 100v to match load
- · Fine Tune knob and LEDs to easily match impedance
- Interrupter feature on Oscillator
- LCD meter on Receiver
- Receiver Loudspeaker or headset use
- Depth determination
- Holiday detection on buried pipe (PD/H)

Construction:

Receiver: Durable and lightweight plastic case Oscillator: Rugged aluminum chassis Carrying Case: New! Rugged, durable case with long life. All components incased in foam for protection during shipping and travelling.

Applications:

- Short Locating
- Holiday Detection (PD/H)
- Line Locating
- Pipe depth determination
- Locate buried insulators
- Locate open couplings
- Locate over water

Recommendations:

Industries:

Gas • Petroleum • Chemicals • Water

Dimensions:

PD Case: 16" x 8" x 20" (40.6 x 20.3 x 50.8cm) PD/Short Shipping Weight: 15 Lbs (6.80 kg) PD/Complete Shipping Weight: 19 Lbs. (8.62 kg)

DELIVERY: Immediately from STOCK

EX-Works San Bernardino, CA USA

SERVICE: 24-hour Turn-Around

TERMS: Net30 Days, on approval of credit

WARRANTY: 90 Days, parts and labor



Available in two configurations:

PD/S (Short) includes: **D** Battery cables (set) (Black / Red)

■ 30' Ground cable (Black)

A Mark IV Receiver

F 6' Oscillator to Pipe cable (Red)

B PD/C Oscillator **C** Headphones

Carrying Case Instruction Manual

PD/H (Holiday Detector) includes all of the above, and these additional components:

- **G** Shoe Cleats (set of 4)
- H Terminal Board (Single)
- **J** 30' Connecting Cable (White)
- Terminal Board (Double)
- K Cleat Cables (set of 4 White)



NEW! Carrying Case

Tough and rugged material, with foam inserts protect the Model PD and all accessories during shipping, storing and transportation

AVAILABLE FROM STOCK